

## Yuasa NP10-6 Industrial VRLA Battery

### Spezifikationen

Nennspannung (V)	6
10-Stunden-Kapazität auf 1,8 V/Zelle bei 20 °C (Ah)	9.2

### Abmessungen

Länge (mm)	151 (±1)
Breite (mm)	50 (±1)
Höhe über den Anschlüssen (mm)	97.5 (±2)
Gewicht (kg)	1.93

### Anschlusspol Typ

Faston - Steckanschluss (JST, sofern angegeben)	4.75
---	------

### Betriebstemperaturbereich

Lagerung (in voll geladenem Zustand)	-20°C to +60°C
Ladung	-15°C to +50°C
Entladung	-20°C to +60°C

### Lagerung

Selbstentladung pro Monat bei 20°C in % (ca.)	3
---	---

### Gehäusematerial

Standard	ABS (UL94:HB)
FR-Version erhältlich	UL94:V0

### Ladespannung

Schwebeladespannung bei 20°C (V)/Block	6.825 (±1%)
Schwebeladespannung bei 20°C (V)/Zelle	2.275 (±1%)
Ladespannungskompensationsfaktor bei Schwebeladung bei Abweichungen von der Standardtemperatur 20°C(mV)	-3
Zyklische oder Starkladespannung bei 20°C (V)/Block	7.26 (±3%)
Zyklische oder Starkladespannung bei 20°C (V)/Zelle	2.42 (±3%)
Ladespannungskompensationsfaktor bei Starkladung bei Abweichungen von der Standardtemperatur 20°C (mV)	-4

### Ladestrom

Ladestrombegrenzung bei Schwebeladung (A)	No limit
Ladestrombegrenzung bei Starkladung (A)	2.5

### Maximaler Entladestrom

1 Sekunde (A)	300
1 Minute (A)	48

### Impedanz

Gemessen bei 1 kHz (mΩ)	8
-------------------------	---

### Gebrauchsdauer und Zulassungen

EUROBAT-Klasse: Standard Commercial	3 to 5 years
YUASA-Gebrauchsdauer bei 20°C (Jahre)	up to 5

distributed by:




PSD POWER STORAGE DEUTSCHLAND GmbH  
Raiffeisenstraße 10  
D-61250 Usingen  
☎ +49 (0)6081 96582-0  
✉ info@psd-power.de  
www.psd-power.de

Irrtümer und Änderungen vorbehalten.  
Datenblatt erstellt am 10/05/2023 - E&EO



### Layout



### Zertifikate von unabhängigen Institutionen

ISO 9001 - Quality Management System



### Sicherheit

#### Einbau

Kann in beliebiger Lage installiert und betrieben werden, außer dauerhaft über Kopf.

#### Tragegriffe

Batterien nicht dauerhaft an den Tragegriffen hängend (sofern vorhanden) installieren.

#### Ventile

Um den Gasdruck auszugleichen, ist jede Zelle mit einem Niederdruck-Ablassventil ausgestattet, das nach dem Öffnen wieder schließt.

#### Gasung

VRLA Batterien setzen Wasserstoffgas frei

#### Recycling

Yuasa VRLA Batterien müssen am Ende ihrer Gebrauchsdauer gemäß den lokalen und nationalen Gesetzen und Richtlinien dem Recycling zugeführt werden.



# Yuasa Technical Data Sheet



## Yuasa NP10-6 Industrial VRLA Battery

### Specifications

Nominal voltage (V)	6
10-hr rate Capacity to 1.8V/Cell at 20°C (Ah)	9.2

### Dimensions

Length (mm)	151 (±1)
Width (mm)	50 (±1)
Height over terminals (mm)	97.5 (±2)
Mass (kg)	1.93

### Terminal Type

FASTON - Quickfit / release (JST where stated)	4.75
--	------

### Operating Temperature Range

Storage (in fully charged condition)	-20°C to +60°C
Charge	-15°C to +50°C
Discharge	-20°C to +60°C

### Storage

Capacity loss per month at 20°C (% approx.)	3
---	---

### Case Material

Standard	ABS (UL94:HB)
FR version available	UL94:V0

### Charge Voltage

Float charge voltage at 20°C (V)/Block	6.825 (±1%)
Float charge voltage at 20°C (V)/Cell	2.275 (±1%)
Float Chg voltage tmp correction factor from std 20°C (mV)	-3
Cyclic (or Boost) charge Voltage at 20°C (V)/Block	7.26 (±3%)
Cyclic (or Boost) charge Voltage at 20°C (V)/Cell	2.42 (±3%)
Cyclic Chg voltage tmp correction factor from std 20°C (mV)	-4

### Charge Current

Float charge current limit (A)	No limit
Cyclic (or Boost) charge current limit (A)	2.5

### Maximum Discharge Current

1 second (A)	300
1 minute (A)	48

### Impedance

Measured at 1 kHz (mΩ)	8
------------------------	---

### Design Life & Approvals

EUROBAT Classification: Standard Commercial	3 to 5 years
Yuasa design life at 20°C (yrs)	up to 5

distributed by:



PSD POWER STORAGE DEUTSCHLAND GmbH  
Raiffeisenstraße 10  
D-61250 Usingen  
☎ +49 (0)6081 96582-0  
✉ info@psd-power.de  
www.psd-power.de

Irrtümer und Änderungen vorbehalten.

Data Sheet generated on 10/05/2023 – E&OE



### Layout



### 3rd Party Certifications

ISO9001 - Quality Management Systems

## Safety

### Installation

Can be installed and operated in any orientation except permanently inverted.

### Handles

Batteries must not be suspended by their handles (where fitted).

### Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

### Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.

